

2-inch exit ferrite magnet compression driver

- 800Hz recommended min. crossover freq (12dB/oct)
- Single piece titanium diaphragm and surround

200W

Continuous
power rating

107dB

sensitivity

3in

Edgewound clad
copper voice
aluminium coil

General Specifications

Power Rating	100W
Continuous power rating	200W
Rated impedance	8 ohm
Sensitivity	107dB
Frequency range	500-18,000Hz
Recommended min. crossover (12 dB/oct)	800Hz
Magnet type	Ferrite
Voice coil diameter	75mm / 3in
Voice coil material	Edgewound copper clad aluminium
Diaphragm material	Titanium
Surround material	Titanium

Mounting Information

Width	180mm / 7.0in
Depth	68.0mm / 2.7in
Fitting	Bolt (4 x M6 holes on a 102mm/4in PCD)
Throat exit	50mm / 2in
Unit weight	4.9kg / 10.8lb

Packed Dimensions & Weight

Single pack size W x D x H	214mm x 196mm x 82mm / x 8.4in 7.7in x 3.2in
Single pack weight	5.1kg / 11.2lb

Repair kits

T6509	Diaphragm repair kit 8 ohm
-------	----------------------------

