

### CDX14-3040

1.4-inch exit neodymium magnet compression driver



- 1,000Hz recommended min. crossover freq (12dB/oct)
- Single piece titanium diaphragm and surround

### General Specifications

Power Rating	75W
Continuous power rating	150W
Rated impedance	8 $\Omega$
Sensitivity	106.5dB
Frequency range	500-18,000Hz
Recommended min. crossover	1000Hz
(12dB/oct)	
Magnet type	Neodymium
Voice coil diameter	75mm / 3in
Voice coil material	Edgewound copper clad aluminium
Diaphragm material	Titanium
Surround material	Titanium
Additional impedances	16?

### Mounting Information

Width	135mm / 5.3in
Depth	68mm / 2.7in
Fitting	Bolt (4 x M6 holes on 102mm/4in PCD)
Throat exit	35mm / 1.4in
Unit weight	1.4kg / 3.1lb

